



## wBridge





## wBridge

wBridge is a smart plug that works with Wi-Fi and Bluetooth. Its function is to remotely operate Watchman Door devices and the internal relay to activate/deactivate the circulation of the Watchman Door.

This device incorporates:

- **Connectivity** Wi-Fi de 2.4Ghz.
- Connectivity Bluetooth Low Energy to link to other Watchman Door devices and set up Wi-Fi.

The wBridge device supports up to 1 linked device and is prepared for 230VAC 50/60Hz power supply.

## **Technical specifications**

Especificación	Parámetro	Medida
Electrónica	Entrada	230VAC, 50/60HZ
	Salida	230VAC, 16A máx
	Temperatura de funcionamiento	0 °C~ 40 °C ( 32°F ~ 104°F )
	Humedad	0% $\sim$ 95% (Sin condensación)
Wi-Fi	Frecuencia	2.4GHz-2.5Ghz (2400MHz- 2483.5MHz)
	Protocolo	802.11 b/g/n
	Potencia de transmisión	13dB@802.11n; 18.5dB@802.11b
Bluetooth	Estándar de Bluetooth	Bluetooth 4.2
	Distancia máxima de conexión	130 metros en espacio abierto
	Capacidad de escaneo	Máximo de 30 dispositivos por BLE
	Sensibilidad de recepción	-97dB

## **LED Specifications**

If the LED is yellow 📀 , it is trying to connect to the Wi-Fi network.

Once the device has been able to connect to the network, the LED will turn green. $^{\textcircled{1}}$ 

If it fails to connect to the network, the LED will turn red.

By pressing the button for 5 seconds the LED will change to blue, the user can set or modify the Wi-Fi network of his device from the App.



+34 937 378 104 info@watchman.es C/ Comadrán, 39 Nave 3 - Pol. Ind. Can Salvatella Barberà del Vallès - Barcelona - España



watchmandoor.com